University of Nebraska - Lincoln

DigitalCommons@University of Nebraska - Lincoln

Faculty Publications from the Department of
Electrical and Computer Engineering

Electrical & Computer Engineering, Department
of

7-2010

A Single Chip Computational Sensor System for Neutron Detection Applications

Nathan R. Schemm

University of Nebraska at Lincoln, nathan.schemm@huskers.unl.edu

Sina Balkir

University of Nebraska-Lincoln, sbalkir@unl.edu

Michael Hoffman

University of Nebraska-Lincoln, mhoffman1@unl.edu

Mark Bauer

University of Nebraska-Lincoln, mark@engr.unl.edu

David Schultz

Wright Patterson Air Force Base, dsschult@andrew.cmu.edu

See next page for additional authors

Follow this and additional works at: <https://digitalcommons.unl.edu/electricalengineeringfacpub>

Part of the [Computer Engineering Commons](#), and the [Electrical and Computer Engineering Commons](#)

Schemm, Nathan R.; Balkir, Sina; Hoffman, Michael; Bauer, Mark; Schultz, David; Petrosky, James C.; McClory, John W.; Natta, Marcus; Brand, Jennifer I.; Tang, Jinke; and Wang, Wendong, "A Single Chip Computational Sensor System for Neutron Detection Applications" (2010). *Faculty Publications from the Department of Electrical and Computer Engineering*. 529.

<https://digitalcommons.unl.edu/electricalengineeringfacpub/529>

This Article is brought to you for free and open access by the Electrical & Computer Engineering, Department of at DigitalCommons@University of Nebraska - Lincoln. It has been accepted for inclusion in Faculty Publications from the Department of Electrical and Computer Engineering by an authorized administrator of DigitalCommons@University of Nebraska - Lincoln.

Authors

Nathan R. Schemm, Sina Balkir, Michael Hoffman, Mark Bauer, David Schultz, James C. Petrosky, John W. McClory, Marcus Natta, Jennifer I. Brand, Jinke Tang, and Wendong Wang

A Single Chip Computational Sensor System for Neutron Detection Applications

Nathan Schemm, Sina Balkir, Michael W. Hoffman, Mark Bauer, David Schultz, James C. Petrosky, John W. McClory, Marcus Natta, Jennifer I. Brand, Jinke Tang, and Wendong Wang

Abstract—This paper presents the design and test results of a standalone computational radiation sensor system based on a single chip solution. A low-power sensor front end with a charge sensitive amplifier and an event driven analog-to-digital converter is integrated on the same chip as a dedicated microcontroller to process and bin the data from the neutron detector diode heterojunction according to pulse height. This combination effectively implements a single chip multichannel analyzer with the capability to do further processing of the data in software. The design was fabricated in a 0.18 μm CMOS technology with field tests demonstrating the validity of the approaches taken. The total system power consumption is 24 μW .

Index Terms—Computational sensor, gadolinium, hafnium oxide, multichannel analyzer, neutron detection, radiation detector.

I. INTRODUCTION

THE detection of radioactive materials is an important sensor application that requires a data acquisition and processing system for reliable and low-power operation. In such an application, low-power operation becomes a key issue in order to achieve maximum battery life. While low-power circuit design techniques can provide a degree of battery life extension, the transmission of a single information bit still requires

power that is equivalent to thousands of digital computations. Hence, a key challenge is the mitigation of energy usage for data transmission through on-sensor computation. Integrating sensing with computation and shifting critical computations to an on-board processor can minimize the amount of raw data to be transmitted from the sensor output. This paradigm can lead to significant reduction in sensor system power requirements.

To that end, the design, fabrication and test of a complete computational radiation sensor system with on board processing is presented in this paper. The design integrates a custom low-power microcontroller core, I/O hardware, timers, SRAM, and a bank of quad low-power front ends on a single chip using a 0.18 μm CMOS technology. The front end design is based on a novel charge sensitive amplifier (CSA) which has a significant reduction in power consumption. As compared to earlier work in the open literature [1]–[5], this new design allows the peak current available to the CSA to be more than 20 times the dc bias level by dynamically scaling the bias current during a neutron detection event. This allows the amplifier to remain in the linear region for more accurate detection.

The electronic circuit design migrates the following critical computation tasks of detection into the sensor head: Counting the neutron events, energy bin classification of captured neutrons and pulse height spectra computation, and the dissemination of the results with minimal redundancy. Hence, the presented computational radiation sensor effectively acts as a low bit-rate information source. The single chip solution leads to a fully functional miniaturized radiation sensor, which is a significant improvement over past work on handheld detectors [1] or more cumbersome industry standard NIM or CAMAC bench or rack instrumentation. Furthermore, integrating everything on a single chip, including the processor and power supply, allows for very tight integration of the system components leading to a lower power consumption and smaller size than an alternate solution using some off-the-shelf components.

In Section II, the architecture of the system is described. Section III presents the fabrication of the complete system and the associated test bed development. Various lab and field test results are presented Section IV. Finally, Section V concludes this paper.

II. COMPUTATIONAL RADIATION SENSOR ARCHITECTURE

The design choices have been mainly driven by low power of operation, small area, reliable communication, and robustness constraints. The overall sensor architecture is displayed in Fig. 1. In particular, the sensor analog front end, event driven analog-to-digital converter (ADC), microcontroller core and its

Manuscript received July 07, 2009; revised October 23, 2009 and December 15, 2009; accepted January 02, 2010. Date of current version May 21, 2010. This work was supported in part by the U.S. Department of Energy National Nuclear Security Administration Office of Nonproliferation Research and Engineering (NA-22) under Grant “All Solid-State Wireless Sensor Network for Nuclear Proliferation Detection,” in part by the U.S. Defense Threat Reduction Agency/CXC under Grant MIPR 09-2862, Grant MIPR 06-2310M, and Grant HDTRA1-07-1-0008, and in part by the U.S. Department of Homeland Security, Domestic Nuclear Detection Office under Grant IACRA hshqdc-08-x-00641. The views expressed in this paper are those of the authors and do not reflect the official policy or position of the Air Force, Department of Defense, or the U.S. Government. The associate editor coordinating the review of this paper and approving it for publication was Prof. Giorgio Sberveglieri.

N. Schemm, S. Balkir, M. W. Hoffman, and M. Bauer are with the Department of Electrical Engineering, University of Nebraska-Lincoln, Lincoln, NE 68588-0511 USA (e-mail: nathan.schemm@huskers.unl.edu; sbalkir@unl.edu; mhoffman1@unl.edu; mark@engr.unl.edu).

D. Schultz, J. C. Petrosky, and J. W. McClory are with the Air Force Institute of Technology, Wright Patterson Air Force Base, OH 45433-7765 USA (e-mail: dsschult@andrew.cmu.edu; james.petrosky@afit.edu; John.McClory@afit.edu).

M. Natta and J. I. Brand are with the College of Engineering and Technology and the Nebraska Center for Materials and Nanoscience, University of Nebraska-Lincoln, Lincoln, NE 68588-0511 USA (e-mail: mnatta1@unlserve.unl.edu; jbrand@unl.edu).

J. Tang and W. Wang are with Department of Physics and Astronomy, University of Wyoming, Laramie, WY 82071 USA (e-mail: jtang2@uwyo.edu; wwang3@uwyo.edu).

Color versions of one or more of the figures in this paper are available online at <http://ieeexplore.ieee.org>.

Digital Object Identifier 10.1109/JSEN.2010.2040731

Fig. 1. Computational radiation sensor architecture. The blocks shown comprise the computational radiation sensor and have been included in a test chip using a 0.18 μm CMOS technology.

Fig. 2. CSA topology dynamically scales the dc bias current [6].

associated peripherals have been designed and included in a test chip.

A customized and dedicated low-power microcontroller core, memory, I/O hardware, timers, a low-power analog front end with quad charge sense amplifiers and ADC are housed in this test chip.

- Sensor analog front end:** A circuit using an adaptive biasing scheme that results in significantly reduced power consumption has been developed. The front end is based on a CSA, and its power consumption is critical due to the always-on nature of the neutron sensor. The schematic of the low-power CSA is shown in Fig. 2 [6]. The core of the amplifier is based on a folded cascode circuit configuration. The dc operating currents are set at 1.5 μA through M12 and 0.75 μA through both M10 and M11. The mirroring gain from transistor M2 to M3 is 30. Hence, in the dc case, most of the current through M5 is diverted away from the mirror M2 and instead flows through M1. M1 is present exclusively to increase the dc current through the input transistor M10 and therefore decreases noise. C1 is required for stability. By carefully selecting the bias voltages, a wide swing can be obtained. During a particle detection event, the small signal current through M10 increases. As in a conventional folded cascode configuration, the current through M11 then decreases. The current through M2 also increases, which is amplified by the mirroring gain from transistor M2 to M3, before being applied to the output.

Thus, the bias current is dynamically scaled during a particle detection event and the peak current is allowed to be more than 20 times the dc bias level by utilizing this adaptive bias scheme. This mechanism permits the amplifier to stay in the linear region allowing more accurate characterization of detection events.

The output swing can be as large as $V_{DD} - 4V_{ov}$, where V_{ov} is the overdrive voltage of the transistors. The dc output level is controlled by V_{ref} . The closed loop charge-to-voltage conversion gain can be approximated as $1/C_{fb}$, where C_{fb} is adjustable in this design to range from 0.2 pF to 15.2 pF in 1 pF increments. The time constant of the circuit can be tuned by adjusting the voltage V_{fb} .

- Integration of sensor front end with an event driven ADC:** A block diagram of the completely developed sensor front end is shown in Fig. 3. The programmability of the front end is implemented via DACs to control the detection threshold and the feedback resistor value. The adjustable feedback capacitor is also shown. Following the CSA, a peak detector circuit captures the peak value of each detection event which is then converted to a digital value via an 8 bit charge-redistribution successive approximation ADC. The comparator Cmp 1 detects when the CSA output goes above its normal quiescent point. When this happens, the ADC trigger line goes low. This also turns M1 and Cp into a peak detector. Internally, the ADC begins to power up and track the input. After the particle event, the ADC begins its conversion on the peak value, and the peak detector returns to tracking the input again. Cc is used to eliminate the dc bias present on the CSA output. The ADC is shut off in between detection events to further reduce power consumption. Fig. 3 shows the architecture of the ADC. It is a standard successive approximation architecture with a buffer on the front and an input signal range from 0 to Ref. It uses a clocked comparator which minimizes power consumption, and the input buffer is shut off after the sampling stage to further conserve power. Not shown, a digital section for the ADC controls the switches to sequence the conversion.

Initial work on the development of the complete low-power front end section for particle detection applications was presented by the authors in [7]. While the earlier work was based on a prototype development using a 0.35 μm CMOS technology, the current design is based on a 0.18 μm CMOS technology with significant reduction in power consumption and overall performance improvement in the circuit specifications. In the current design, the entire circuit consumes between 4 μW and 20 μW of power depending on the particle detection rate. The peak ADC conversion rate, and therefore particle detection rate, is 400 K samples per second. The conversion energy is 75 pJ per conversion. This low-power operation enables the development of compact, long-life, battery powered, remote particle sensors.

The digital interface for the ADC consists of a 16 byte FIFO buffer. This is present to decrease the frequency at which the processor must be interrupted to process the neutron detection events. This is important when using dy-

Fig. 5. Overall computational sensor chip layout.

shuts off M2 when the current through it drops to zero. The DAC allows the output voltage to be changed, and the following buffer has a slow slew rate to implement soft-start. The complete design is presented in [8].

A clock system is also required. A low-power 32 kHz crystal oscillator similar to that presented in [9] is used as the time base. This is the only active clock for the majority of the time. This is used to schedule processor wakeup intervals and timekeeping functions. The ADC generates its own internal clock when needed, so it does not require a system clock. When the processor is active, a digitally controlled oscillator is used as the system clock. This low-power oscillator starts up very quickly, and is internally stabilized by the 32 kHz crystal oscillator.

These blocks comprise the computational radiation sensor. Fig. 5 displays the layout of the main functional sections of the chip.

III. FABRICATION OF COMPUTATIONAL RADIATION SENSOR SECTION AND TEST BED DEVELOPMENT

A 3 mm × 3 mm chip based on a 0.18 μm CMOS technology, containing the blocks indicated in the previous section has been fabricated. Fig. 6 displays the die photo of the fabricated chip. The test bed architecture for the chip is shown in Fig. 7. This includes an interface to the external semiconductor diode neutron sensors as well as an interface to the computer via a USB to serial communications device. The serial flash stores the program for the internal RISC microcontroller, as the fabrication process used does not support integrated flash memory. At boot, the 2 kB boot ROM contains a program to copy the user program from the external serial flash to the internal SRAM and execute that program. The timers are used for timekeeping functions, and can operate on the always-active crystal oscillator clock. The system and power control module also includes a watchdog timer if required for system reliability. In the analog front end, the analog signals can be extracted or inserted at various places along the signal chain for maximum flexibility in testing.

The fabricated test bed PCB is shown in Fig. 8, where the computational radiation sensor chip is clearly visible in

Fig. 6. Fabricated computational sensor chip.

Fig. 7. Computational sensor architecture.

the center of the PCB. A coin-type lithium battery can be mounted on the back of the PCB. The overall dimensions are 3.5 cm × 6 cm × 1.6 cm including the battery.

A self-contained computational radiation sensor operation is required as part of this detection scheme. To that end, a software development environment has been devised using the test bed developed for this purpose. While the developed software does not lead to a full operating system, it is more of a shell to provide an environment that enables the individual developing the system full access to all I/O and memory locations without needing to recompile and reprogram the chip. In addition, the software allows additional features and functions to be added by using simple commands. Communications with the processor is done with a 3 V USB to serial communications device. The use

Fig. 8. Test bed PCB.

Fig. 9. Sample histogram acquired.

of USB allows almost any computer systems to be used for development. The software written for this system is a subset of the Forth programming language. This was chosen because of its ability to operate in a very restricted memory footprint. The entire Forth system requires only 8 kbytes of memory.

In the Forth system, actions are done with two different types of codes, native and interpreted. The native codes are in the binary language of the microprocessor and generated with a *gcc* compiler. A basic set of codes, some native and some interpreted, exist immediately after booting. These basic codes include math, simple I/O, memory management, time keeping, looping, and a compiler. The compiler is used to add additional functionality.

IV. LAB AND FIELD TESTS

A. Lab Tests

The pulse height spectra gathering application has been developed and implemented on the single chip computational radiation sensor to demonstrate the functionality of the software environment during lab tests. With an 8-bit ADC resolution, the application uses 256 separate counters to keep track of how many neutron events occurred with each pulse height. A plot of those counters produces a histogram of the neutron counts. Using an arbitrary waveform generator, a sequence of pulses with three distinct amplitudes with different arrival rates were applied to the analog front end of the computational sensor chip. Fig. 9 displays a sample pulse height spectra with 256 bins generated by the Forth system running on the chip.

TABLE I
DESIGN SPECIFICATIONS

Process:	0.18 μm
Area:	9 mm^2
Front End Power Consumption:	$4 + 0.075 \times R \mu\text{W}^a$
CSA Feedback Capacitance:	0.2 - 15.2 pF in 1 pF increments
Max Particle Detection Rate:	$4 \times 10^5 \text{ sec}^{-1}$
Equivalent noise charge, detector disconnected, $C_{fb}=0.2 \text{ pF}$:	525 e^-
ADC Type:	Charge Redistribution SAR
ADC Bits:	8
ADC Conversion Energy Consumption:	75 pJ
Max Processor Frequency:	60 MHz
Processor Voltage Active:	0.9-1.8 V
Processor Voltage Sleep:	0.65-1.8 V
Processor Active Power:	100-300 $\mu\text{W/MHz}^b$
Processor Sleep Power:	2.5-9 μW^b
Crystal Oscillator, Biases and References Total Power Consumption:	3 μW
Battery Voltage:	3 V
Battery Capacity:	3 WHr
Total Computational Sensor Average Power Consumption:	24 μW^c
Battery Life:	> 10 Years

^a R is particle rate in thousands particles/sec.

^b Power varies depending on DVS voltage setting.

^c With single channel active, 4 μW for each additional channel.

To minimize the power consumption, the processor is in sleep mode over 99.9% of the time. The main digitally controlled oscillator is disabled during this time, except for when a character transmission to or reception from the computer is occurring. With the clock disabled, the digital circuitry only consumes between 2.5 and 9 μW of power depending on the supply voltage. The 32 kHz crystal oscillator operates continually. The main digital supply is operated at 900 mV to further reduce power consumption. The analog front end only wakes the processor when 12 or more unprocessed neutron events are in one of the FIFOs. When the processor wakes, it processes all the events in all four FIFOs, and then returns to the sleep state.

Table I gives some relevant specifications obtained from measurements of the chip.

B. Field Tests and Discussion of Results

Neutron field tests were conducted with a paraffin moderated 5.2 curie plutonium-beryllium neutron source which provided 2.2×10^4 thermal to epithermal neutrons/cm²-second, as calibrated by foil activation methods. Fig. 10 displays the actual test setup used in the testing of the computational sensor. As the front end CSA design is well suited for semiconductor neutron detectors [10], heterojunction diodes composed of mixed gadolinium and hafnium oxide (GdHfO_2) on silicon have been utilized as the neutron sensing devices in this work [11]. In particular, the diodes that were utilized in the field tests are constructed with slightly less than 100 nm oxides of 15% gadolinium and 75% hafnium oxide films that were deposited on n-type single crystal Si(100) substrates using pulsed laser deposition [11], [12].

The absorption of the neutron leaves the ^{158}Gd in an excited state that releases energy through emission of high energy

Fig. 10. Field test setup.

Fig. 11. Charge sensitive amplifier output waveforms.

gamma rays, low-energy gamma rays, X-rays, internal conversion (IC), and Auger Coster-Kronig (ACK) conversion electrons as

During a neutron capture event, the conversion electrons generate charge pulses in the heterojunction diodes which are converted to voltage by the front end section of the computational sensor.

Typical charge sensitive amplifier output waveforms captured over a period of 1 ms by the sensor system are shown in Fig. 11. The waveforms show several large spikes resulting from neutron detection at a charge-to-voltage gain setting of $833 \mu\text{V}/\text{fC}$, corresponding to 1.2 pF of integration capacitance with an amplifier time constant setting of $20 \mu\text{s}$. A diode reverse bias level of 2 V has been used with a bias resistor value of $20 \text{ k}\Omega$ during the experiments.

For the pulse height spectra gathering, 256 histogram bins were created using an incremental bin resolution of 5.64 fC/bin , which corresponds to 4.7 mV after charge-to-voltage conversion. The experimental pulse height spectrum is shown in Fig. 12. Following electronic suppression of pulses below 170 mV , which dominate the pulse height collection without electronic suppression, the main contributions to the detection signal come from the conversion electron and the Gd k-shell Auger electron resonances. For ^{158}Gd , the current pulses generated by 79.5 keV (and other) conversion electrons can be efficiently measured and reliably identified. The K-shell binding energy is 50.2 keV resulting in a variety of Auger electron resonances of decreasing kinetic energy, ending in the 29.3 keV conversion electron centered pulse [13]. The K-shell electron excitation is accompanied by a 44 keV X-ray [13]–[15] which is not identified in the spectra in Fig. 12. The M shell

Fig. 12. Pulse height spectra of 15% Gd doped HfO_2 on n-type Si(100) with thermalized neutrons from a PuBE source.

binding energy is 1.8 keV , resulting in only a small reduction of the 79.5 conversion electron energy to about 77 keV . Overall the pulse height spectra results in the creation of 40 to 80 keV pulses largely for $^{157}\text{Gd}(n, \gamma)$ that are in good agreement with the model calculations. The features in the experimental spectra can be assigned to specific expected K-shell Auger resonances, but with a nonuniform distribution over this range [13].

To provide a comparison with theory, the devices have been simulated using the Monte Carlo N-Particle Transport Code (MCNP5.0) [16], where a planar source of 10^{11} neutrons was assumed and a model neutron spectrum was calculated from 30 eV to 14 MeV . To better compare experiment with the model simulations, there are corrections at the low energy end of the model pulse height spectra to account for the large number of counts rejected by electronic noise and signal suppression below a 170 mV pulse height in the experiment. By incorporating these corrections to the model, there is considerable agreement between experimental and theoretical pulse height spectra displayed in the bottom portion of Fig. 12. The deviations observed between simulation and experiment at larger pulse heights can be attributed to incomplete charge collection due the fact that the 15% Gd doped HfO_2 film is rather thin.

It should be noted that the presented prototype system is not radiation hardened, thus it will be affected by radiation striking the electronics. Fast neutrons may cause crystal defects which accumulate slowly over time to eventually cause permanent circuit failure and thermal neutrons may cause single-event upset errors. The software includes a watchdog timer to facilitate recovery from such software errors.

Other neutron detection technologies exist [17], most of which could be directly interfaced to the electronics with minimal hardware modifications. Table II shows a comparison of selected technologies.

All of the detection technologies except the solid-state one require a high voltage supply to bias either the detector itself or the photomultiplier tube (PMT). These supplies range from 500 V to 3 kV which dramatically increases system power consumption. Furthermore, the detector or PMT are fragile elements which are not suitable for harsh environments. The solid-state neutron detectors such as the presented GdHfO_2 detector do not require the high voltage supply and are therefore particularly suited to low-power applications [18].

TABLE II
DETECTION TECHNOLOGIES

Technology	Detection Probability			Power
	Thermal Neutron	Fast Neutron	γ -ray	
BF ₃ Tubes	high	low	moderate	moderate
³ He Tubes	very high	low	low	moderate
⁴ He or CH ₄	low	high	moderate	moderate
Fission Chamber	low	low	very low	moderate
Plastic Scintillator	high	very high	very high	high
Solid-State	high	low	moderate	low

V. CONCLUSION

A miniaturized computational radiation sensor that effectively acts as a low bit-rate information source has been developed based on a 0.18 μm CMOS technology. The electronic circuit design migrates the following critical computation tasks of detection into the sensor head: counting the neutron events, energy bin classification of captured neutrons and pulse height spectra computation, and the efficient dissemination of the results via existing communication interfaces. Hence, the presented standalone integrated sensor paradigm relaxes the data transmission requirements and opens up possibilities for achieving low-power wireless sensor network operation. Fully integrating all the components of the design allows for a lower overall power consumption than a solution using some off-the-shelf components, allowing a battery life of over ten years. Lab measurements and field tests have confirmed the operation of the chip and the validity of the approaches taken.

ACKNOWLEDGMENT

The authors would like to thank Dr. R. Fairchild for his assistance with field testing.

REFERENCES

- [1] K. Osberg, N. Schemm, S. Balkir, J. Brand, S. Hallbeck, P. Dowben, and M. Hoffman, "A handheld neutron-detection sensor system utilizing a new class of boron carbide diode," *IEEE Sensors J.*, vol. 6, no. 6, pp. 1531–1538, Dec. 2006.
- [2] T. Noulis, S. Siskos, and G. Sarraayrouse, "Noise optimized charge-sensitive CMOS amplifier for capacitive radiation detectors," *IET Cir. Dev. Syst.*, vol. 2, no. 3, pp. 324–334, Jun. 2008.
- [3] J. Kaplon and W. Dabrowski, "Fast CMOS binary front end for silicon strip detectors at LHC experiments," *IEEE Trans. Nucl. Sci.*, vol. 52, no. 6, pp. 2713–2720, Dec. 2005.
- [4] Z. Yacong, C. Zhongjian, L. Wengao, J. Lijiu, and Z. Baoying, "Design and test results of a front-end ASIC for radiation detectors," in *Proc. Int. Conf. Solid-State IC Tech. 2008*, Oct. 2008, pp. 1717–1720.
- [5] S. Tadjia, J. Spiegel, and H. Williams, "A CMOS low noise and low power charge sampling integrated circuit for capacitive detector/sensor interfaces," *IEEE J. Solid-State Circuits*, vol. 30, no. 2, pp. 110–119, 1995.
- [6] N. Schemm, S. Balkir, and M. W. Hoffman, "A low-power CMOS front end for particle detection applications," in *Proc. IEEE Int. Symp. Circuits Syst. (ISCAS) 2008*, Seattle, WA, May 2008, pp. 1866–1869.
- [7] N. Schemm, S. Balkir, M. W. Hoffman, and M. Bauer, "A computational sensor system for particle detection applications," in *Proc. IEEE Int. Symp. Circuits Syst. (ISCAS) 2009*, Taipei, Taiwan, May 2009, pp. 2169–2172.
- [8] N. Schemm, S. Balkir, and M. W. Hoffman, "The design of an ultra-low power buck regulator supporting dynamic voltage scaling for wireless sensor networks," in *Proc. IEEE Int. Symp. Circuits Syst. (ISCAS) 2009*, Taipei, Taiwan, May 2009, pp. 828–831.
- [9] E. A. Vittoz, M. G. R. Degrauwe, and S. Bitz, "High-performance crystal oscillator circuits: Theory and application," *IEEE J. Solid-State Circuits*, vol. 23, no. 3, pp. 774–783, Jun. 1988.

- [10] A. Caruso, P. Dowben, S. Balkir, N. Schemm, K. Osberg, R. Fairchild, O. Barrio Flores, S. Balaz, A. Harken, B. Robertson, and J. Brand, "The all boron carbide diode neutron detector: Comparison with theory," *Mater. Sci. Eng. B*, vol. 135, no. 2, pp. 129–133, Nov. 2006.
- [11] I. Ketsman, Y. B. Losovyj, A. Sokolov, J. Tang, Z. Wang, M. Natta, J. I. Brand, and P. A. Dowben, "Gd-doping of HfO₂," *Appl. Surf. Sci.*, vol. 254, no. 14, pp. 4308–4312, May 2008.
- [12] Y. B. Losovyj, I. Ketsman, A. Sokolov, K. D. Belashchenko, P. A. Dowben, J. Tang, and Z. Wang, "The electronic structure change with Gd doping of HfO₂ on silicon," *Appl. Phys. Lett.*, vol. 91, p. 132908, 2007.
- [13] Y. Sakurai and T. Kobayashi, "Experimental verification of the nuclear data of gadolinium for neutron capture theory," *J. Nucl. Sci. Tech.*, vol. Sup. 2, pp. 1294–1297, Aug. 2002.
- [14] R. C. Greenwood, C. W. Reich, H. A. Baader, H. R. Koch, D. Breitig, O. W. Schult, B. Fogelberg, A. Backlin, W. Mampe, T. V. Egidy, and K. Schreckenbach, "Collective and two-quasiparticle states in ¹⁵⁸Gd observed through study of radiative neutron capture in ¹⁵⁷Gd," *Nucl. Phys. A*, vol. 304, no. 2, pp. 327–428, Jul. 1978.
- [15] P. L. Reeder, "Thin GSO scintillator for neutron detection," *Nucl. Instrum. Meth. Phys. Res. A*, vol. 353, pp. 134–136, 1994.
- [16] MCNP-A General Monte Carlo N-Particle Transport Code, Version 5 – Volume I: Overview and Theory X-5 Monte Carlo Team, 2003, LA-UR-03-1987.
- [17] T. W. Crane and M. P. Baker, "Neutron Detectors," in *Passive Non-destructive Assay of Nuclear Materials*. Springfield, VA: Natl. Tech. Inf. Serv., 1991, pp. 379–406.
- [18] A. Miresghhi, G. Cho, J. S. Drewery, W. S. Hong, T. Jing, H. Lee, S. N. Kaplan, and V. Perez-Mendes, "High efficiency neutron sensitive amorphous silicon pixel detectors," *IEEE Trans. Nucl. Sci.*, vol. 41, no. 4, pp. 915–921, Aug. 1994.

Nathan Schemm received the B.S. degree in electrical engineering from the University of Nebraska, Lincoln, in 2006, where he is currently working towards the Ph.D. degree.

His research interests include VLSI integration of wireless sensor networks. He has worked on a new class of boron carbide diodes for neutron detection applications and is especially interested in the integration of such diodes into a wireless sensor network. Other research interests include CMOS imagers with focal plane image processing and compression, cellular neural networks, power electronics design, and ultra-wideband technology.

Sina Balkir received the B.S. degree in electrical engineering from Boğaziçi University, Istanbul, Turkey, in 1987. He received the M.S. and Ph.D. degrees in electrical engineering from Northwestern University, Evanston, IL, in 1989 and 1992, respectively.

Between 1992 and 1998, he was with the Department of Electrical and Electronics Engineering, Boğaziçi University, working as an Assistant and Associate Professor. He is currently with the Department of Electrical Engineering, University of Nebraska, Lincoln, where he serves as a Professor.

His research interests include CAD of VLSI systems, analog VLSI design automation, and focal plane computation arrays for image processing.

Michael W. Hoffman received the B.S. degree from Rice University, Houston, TX, the M.S. degree from the University of Southern California, Los Angeles, and the Ph.D. degree from the University of Minnesota, Twin Cities, all in electrical engineering.

From 1985 to 1988, he was a Signal Processing System Engineer in the Space Communications Division, TRW, Inc. In 1993, he joined the University of Nebraska, Lincoln, where he currently serves as a Professor. His research interests include data compression, joint source channel coding, and

sensor array processing.

Mark Bauer received the B.S. degree in computer science from the University of Nebraska, Lincoln, in 1980 and the M.S. and Ph.D. degrees in electrical engineering from the University of Nebraska, in 1989 and 2001, respectively.

He has 25 years of experience in design and manufacturing of products using embedded microcontrollers. Since 2006, he has been an instructor with University of Nebraska in the Electrical Engineering Senior Design Program.

Marcus Natta received the B.S. degree in physics from Cameron University, Lawton, OK, in 2002 and the Ph.D. degree in chemical and materials engineering from the University of Nebraska, Lincoln, in 2008.

His research interests include novel materials characterization and device fabrication for advanced power conversion and radiation detection applications.

David Schultz is currently pursuing the B.S. degree in physics at the Department of Physics, Carnegie Mellon University, Pittsburgh, PA.

His research interests include neutron detection sensor design, and the testing of such designs using computer simulations. In addition to neutron simulations, he is also interested in computer simulations of other particles.

Jennifer I. Brand received the B.S. and M.S. degrees from the University of Michigan, Ann Arbor, and the Ph.D. degree from the University of California, San Diego.

A traditional chemical engineer with national laboratory and private sector work experience, she is in currently a Professor with the College of Engineering, University of Nebraska, Lincoln. Her research focuses on materials processing for sensors and advanced energy systems.

James C. Petrosky received the B.A. degree from Millersville University of Pennsylvania, Millersville, in 1984, the M.S. degree in engineering physics in 1992, and the Ph.D. degree in engineering physics in 1995 from Rensselaer Polytechnic Institute, Troy, NY.

From 1984 to 2004, he served as an Engineer Officer the U.S. Army and taught physics and nuclear engineering at the U.S. Military Academy from 1992 to 1996. He is currently the Chairman of the Nuclear Engineering Program at the U.S. Air Force Institute

of Technology, Wright Patterson Air Force Base, OH. His research interests include radiation effects on electronics and materials and design and analysis of solid state detectors and sensors.

Jinke Tang received the B.S. degree in physics from Jilin University, China, the M.S. degree in metallurgy and the Ph.D. degree in solid-state physics from Iowa State University, Ames.

He was a faculty member in the Department of Physics, University of New Orleans, for 17 years. He is currently a Professor in the Department of Physics and Astronomy, University of Wyoming, Laramie.

John W. McClory received the B.S. degree in physics from Rensselaer Polytechnic Institute, Troy, NY, in 1984, the M.S. degree in physics from Texas A&M University, College Station, in 1993, and the Ph.D. degree in nuclear engineering from the Air Force Institute of Technology, Wright-Patterson AFB, OH, in 2008.

He has been an active duty Army officer since 1984 with duty as an armor officer and as a nuclear and counterproliferation officer in U.S., Europe, and the Middle East. He was an Instructor and Assistant Pro-

fessor of Physics at the United States Military Academy from 1993 to 1996. He is currently an Assistant Professor of Nuclear Engineering at the Air Force Institute of Technology assigned to the Defense Threat Reduction Agency.

Wendong Wang received the B.S. degree in physics and the Ph.D. degree in materials physics from the University of Science and Technology, Beijing, China.

After two years of postdoctoral research at the same institution, he joined the Physics Department, University of New Orleans, as a Postdoctoral Research Associate. He is now a Research Scientist at the University of Wyoming's Department of Physics and Astronomy.